

Power Amplifier Comparison Chart

	330A	400M	760A	860A v2	888
Number of Channels	2 - Stereo	1 - Mono	2 - Dual-Mono	2 - Dual-Mono	1 - Mono
Power Output - 8Ω	125 W/ch.	400 W	130 W/ch.	225 W/ch.	888 W
Power Output - 4Ω	250 W/ch.	650 W	260 W/ch.	450 W/ch.	1776 W
Power Output - Mono	400 W	n/a	500 W	750 W	n/a
Configuration	Balanced	Balanced	Balanced	Balanced	Balanced
Balanced inputs	●	●	●	●	●
Single-ended inputs	●	●	●	●	●
S/N Ratio @ full power	> 100dB	> 106dB	> 104dB	> 110dB	> 120dB
THD @ 1kHz, full power	< 0.05 %	< 0.05 %	< 0.04 %	< 0.03 %	< 0.04 %
Output Binding Posts	1 pair / ch.	1 pair	1 pair / ch.	1 pair / ch.	2 pairs
RS-232 Port	●	●	●	●	●
12V Trigger Input/Output	1 / 1	1 / 1	1 / 1	1 / 1	1 / 1
Weight (lb)	33	33	45	90	300
Dimensions (w" x h" x d")	16.9 x 3.5 x 14	16.9 x 3.5 x 14	18.8 x 4.0 x 18.1	18.8 x 7.5 x 17.5	22 x 14 x 27

* With 230V AC mains version